

# 马达对应表 (输入转速为3,000RPM时)

## MOTOR MATCHING TABLE (WHEN INPUT SPEED IS 3,000RPM)

### 对应表 Matching Table

生产厂家 Motor Manufacturer	马达系列 Motor Series	马达功率 Motor Power(W)				
		50W	100W	200W	400W	750W
松下电器产业(株) Panasonic	MSM	T1				
	MSMA	T1				
	MSMD	T1				
	MUMA	标准外 Out Of Standard	标准外 Out Of Standard	T1		
	MBMK	T1	标准外 Out Of Standard	T1		
	MUMS	标准外 Out Of Standard				
(株)安川电机 Yaskawa Electric	SGM	T2				
	SGMAH	T2				
	SGMAS	T2				
	SJME	无对象 No Subject	T2			
	SGMJV	T3				
	SGMAV	T3				
三菱电机(株) Mitsubishi Wlectric	HC-KF	T3				
	HC-KFS	T3				
	HC-MF	T3				
	HC-MFS	T3				
	HA-ME	T3				
	HC-PQ	T3				无对象 No Subject
	HC-KQ	T3				无对象 No Subject
	HF-KP	T3				
欧姆龙(株) Omron	R88M-U	T2				
	R88M-W	T2				
	R7M-A	T2				
	R7M-Z	T2				
富士电机机器控制(株) Fuji Electric Systems	GYS※	T2				
山洋电气(株) Sanyo Denki	P30B	T3				T2
	Q1	T3				标准外 Out Of Standard
(株)吉恩斯 Keyence	MV	T3				标准外 Out Of Standard
东荣电机(株) Toshiba Machine	VLBSV-Z※	标准外 Out Of Standard			T3	
	VLBSV-ZA※	标准外 Out Of Standard			T3	
	VLBSVT	标准外 Out Of Standard			T3	标准外 Out Of Standard
多摩川精机(株) Tamagawa Seiki	TBL-i※	T3				无对象 No Subject
	TBL-III※	T3				标准外 Out Of Standard
日机电转(株) Nikki Denso	NA50	T1				
	NA70※	T3				无对象 No Subject
	NA80※	T3				标准外 Out Of Standard
(株)三明 Sanmei	TS※	T3				标准外 Out Of Standard
	SS※	T3				标准外 Out Of Standard
(株)日立产机系统 Hitachi Industrial EquipmentSystems	ADMA	T3				标准外 Out Of Standard
三木普利 Miki Pulley	SA3	T1				

注1)没有油封和尺寸不同时，安装带油封的马达有时需特别订货。

If an oil-seal is not present and the size is different, attachment of the oil-seal may correspond to special order, in some cases.

注2)马达轴为D形轴、锥形时需要特别订货。 If the motor shaft is of D-cut and taper type, it corresponds to a special order.

注3)因马达功率 (适用表中带※的马达) 与减速比的组合，出现瞬间最大输出扭矩时，产生的轴向力有时会超过伺服马达容许轴向力，因此，需要注意。

Note that thrust power arising out of instantaneous max. output torque by the combination of motor capacity (motor of the motor series table) and reduction ratio may exceed permissible thrust power of the servo motor.

注4)标准外有时需要特别订货。欲知详情，请另外与本公司联系。

Out-of-standard may correspond to a special order in some cases, For details, contact us.

## 马达对应表 (输入转速为3,000RPM时) MOTOR MATCHING TABLE (WHEN INPUT SPEED IS 3,000RPM)

### 对应表 Matching Table

生产厂家 Motor Manufacturer	马达系列 Motor Series	马达功率 Motor Power(W)								
		1000W	1500W	2000W	2500W	3000W	3500W	4000W	4500W	5000W
松下电器产业(株) Panasonic	MSM	T1								
	MSMA	T1								
(株)安川电机 Yaskawa Electric	SGMS	T2		无对象No Subject		T2	无对象No Subject		T2	T2
	SGMESH	T2		无对象No Subject		T2	无对象No Subject		T2	T2
	SGMSS	T2				无对象No Subject		T2	无对象No Subject	
三菱电机(株) Mitsubishi Wlectric	HC-RF	T3		无对象No Subject		T3	无对象No Subject		T3	T3
	HC-RFS	T3		无对象No Subject		T3	无对象No Subject		T3	T3
	HC-RP	T3		无对象No Subject		T3	无对象No Subject		T3	T3
欧姆龙(株) Omron	R88M-U	T2		无对象No Subject		T2	无对象No Subject		T2	T2
	R88M-W	T2		无对象No Subject		T2	无对象No Subject		T2	T2
富士电机机器控制(株) Fuji Electric Systems	GS	T3		无对象No Subject		T2	无对象No Subject		T2	T2

### 下列系列马达也可以标准方式适应 Standard Compatibility With The Following Motor Series

生产厂家 Motor Manufacturer	马达系列 Motor Series	马达功率 Motor Power(W)
三菱电机(株) Mitsubishi Wlectric	HC-SFS※	500W,1000W,1500W,2000W,3500W
	HF-SP	
(株)安川电机 Yaskawa Electric	SGMP	100W,200W,400W,750W,1500W
	SGMPH	
	SGMPS	
松下电器产业(株) Panasonic	MQMA	100W,200W,400W
欧姆龙(株) Omron	R88M-WP	100W,200W,400W,750W,1500W
	R7M-AP	100W,200W,400W,750W
富士电机机器控制(株) Fuji Electric Systems	GYC	100W,200W,400W
发那科(株) Fanuc	BiS※	200W,400W,500W,750W,1200W

注1)没有油封和尺寸不同时,安装带油封的马达有时需特别订货。注2)马达轴为D形轴、锥形时需要特别订货。注3)因马达功率(适用表中带※的马达)与减速比的组合,出现瞬间最大输出扭矩时,产生的轴向力有时会超过伺服马达容许轴向力,因此,需要注意。注4)标准外有时需要特别订货。欲知详情,请另外与本公司联系。

Note1) If an oil-seal is not present and the size is different, attachment of the oil-seal may correspond to special order, in some cases. Note2) If the motor shaft is of D-cut and taper type, it corresponds to a special order. Note3) Note that thrust power arising out of instantaneous max. output torque by the combination of motor capacity (motor of the motor series table) and reduction ratio may exceed permissible thrust power of the servo motor. Note4) Out-of-standard may correspond to a special order in some cases. For details, contact us.

除上述伺服马达厂家外,本公司减速机还适配以下伺服马达厂家。安装方式请咨询本公司。

Our gearbox can match to servo motor of followings manufacturers, including above. Please ask us about the assembly.

神钢电机(株)	日本电产三协	中达电通	路斯特	博世力士乐
FANUC	POCKWELL	山洋	多摩川	基恩斯
东芝机械	日机电装	三明	日立产机系统	三木普利

其他 etc.