

## 标准实际速比 NORMAL RATIO & ACTUAL RATIO

### ■ 标准型 Normal Duty Type

| 速比 Ratio | 低段实际减速比 Actual Ratio |        |        |        |           |       |       |
|----------|----------------------|--------|--------|--------|-----------|-------|-------|
|          | 100W                 | 200W   | 400W   | 750W   | 1500W     | 2200W | 3700W |
| 3        | 3.08                 | 3.08   | 2.96   | 2.93   | 3.14      | 2.99  | 2.99  |
| 5        | 4.88                 | 4.88   | 5.05   | 5.03   | 5.20      | 5.08  | 5.08  |
| 10       | 9.99                 | 9.99   | 10.29  | 9.97   | 10.18     | 10.09 | 10.09 |
| 15       | 14.95                | 14.74  | 15.01  | 15.02  | 15.35     | 15.35 | 14.69 |
| 20       | 19.90                | 20.37  | 20.68  | 19.86  | 20.73     | 20.17 | 19.83 |
| 25       | 24.44                | 25.25  | 25.45  | 24.70  | 25.80     | 25.30 | 25.09 |
| 30       | 30.80                | 32.09  | 30.12  | 30.18  | 30.10     | 29.6  | 31.50 |
| 40       | 40.33                | 40.19  | 39.33  | 40.24  | 39.62     | 38.15 | 39.24 |
| 50       | 50.60                | 51.06  | 50.21  | 50.30  | 51.36     | 49.19 | 49.26 |
| 60       | 61.83                | 62.19  | 59.43  | 60.29  | 59.73     | 59.88 | 60.67 |
| 70       | 72.29                | 72.18  | 69.59  | 69.74  | 69.33     | 70.70 |       |
| 80       | 78.56                | 79.84  | 81.22  | 80.34  | 79.18     | 78.33 |       |
| 90       | 92.67                | 91.04  | 92.5   | 90.17  | 88.53     | 87.35 |       |
| 100      | 102.97               | 98.06  | 99.38  | 98.15  | 99.76     | 98.18 |       |
| 110      | 112.87               | 109.43 | 111.95 | 110.00 |           |       |       |
| 120      | 120.93               | 119.00 | 119.10 | 117.78 | 122.56    |       |       |
| 130      | 132.79               | 132.21 | 129.63 | 132.81 |           |       |       |
| 140      | 143.86               | 142.92 | 138.89 | 139.67 | 137.87    |       |       |
| 150      | 149.39               | 146.63 | 149.51 | 151.93 |           |       |       |
| 160      | 161.84               | 161.15 | 161.97 | 158.93 | ***165.02 |       |       |
| 170      | 165.57               | 173.37 | 168.52 | 170.76 |           |       |       |
| 180      | 182.75               | 176.03 | 183.63 | 179.82 | ***183.82 |       |       |
| 200      | 201.02               | 193.37 | 201.99 | 198.89 | ***206.90 |       |       |

※\*\*\*为达到此速比时, 必须搭配6P马达使用

※\*\*\*It need use 6 pole motor to reach certain ratio

| 速比 Ratio | 高段实际减速比 Actual Ratio |         |         |      |       |       |       |
|----------|----------------------|---------|---------|------|-------|-------|-------|
|          | 100W                 | 200W    | 400W    | 750W | 1500W | 2200W | 3700W |
| 300      | 300.01               | 317.75  | 311.61  |      |       |       |       |
| 400      | 413.34               | 429.11  | 409.45  |      |       |       |       |
| 450      | 453.72               |         |         |      |       |       |       |
| 500      | 508.68               | 534.06  | 513.59  |      |       |       |       |
| 600      | 602.02               | 624.73  | 600.88  |      |       |       |       |
| 700      | 704.76               |         | 679.85  |      |       |       |       |
| 800      | 786.11               | 832.97  | 774.45  |      |       |       |       |
| 900      | 920.42               | 927.57  | 938.27  |      |       |       |       |
| 1000     | 1003.57              | 1041.21 | 1042.61 |      |       |       |       |
| 1100     | 1105.31              |         |         |      |       |       |       |
| 1200     | 1187.86              | 1248.00 | 1212.52 |      |       |       |       |
| 1300     | 1284.40              |         |         |      |       |       |       |
| 1400     | 1390.93              | 1443.62 | 1407.40 |      |       |       |       |
| 1500     | 1516.05              |         |         |      |       |       |       |
| 1600     | 1623.38              | 1663.04 | 1607.35 |      |       |       |       |
| 1700     | 1703.73              |         |         |      |       |       |       |
| 1800     | 1848.84              | 1866.52 | 1797.16 |      |       |       |       |

## 各国电压表 COUNTRIES VOLTAGE

| 国名<br>Country        | 频率<br>Frequency | 单相<br>1-Phase  | 三相<br>3-Phase      | 国名<br>Country          | 频率<br>Frequency | 单相<br>1-Phase | 三相<br>3-Phase      |
|----------------------|-----------------|----------------|--------------------|------------------------|-----------------|---------------|--------------------|
| 中国<br>China          | 50              | 220            | 220/380            | 日本<br>Japan            | 50/60           | 100/200       | 200                |
| 澳洲<br>Australia      | 50              | 240            | 240/415            | 科威特<br>Kuwait          | 50              | 100/200       | 200                |
| 奥地利<br>Austria       | 50              | 220            | 220/380            | 黎巴嫩<br>Lebanon         | 50              | 110/220       | 220/380            |
| 孟加拉<br>Bangladesh    | 50              | 230            | 230/400            | 马来西亚<br>Malaysia       | 50              | 115/240       | 240/415<br>400/440 |
| 比利时<br>Belgium       | 50              | 127/220        | 220/380            | 荷兰<br>Netherlands      | 50              | 110/220       | 220/230            |
| 巴西<br>Brazil         | 50<br>60        | 110/220<br>127 | 220/380            | 纽西兰<br>New Zealand     | 50              | 230           | 230/400            |
| 缅甸<br>Burma          | 50              | 230            | 230/440            | 巴勒斯坦<br>Pakistan       | 50              | 230           | 220/380<br>230/400 |
| 高棉<br>Cambodia       | 50              | 120            | 220/380            | 沙乌地阿拉伯<br>Saudi-arabia | 50<br>60        | 127/220       | 110/220<br>127     |
| 智利<br>Chile          | 50              | 220            | 220/380            | 叙利亚<br>Syris           | 50              | 115/200       | 220/380            |
| 阿根廷<br>Argentina     | 50              | 220            | 220/380            | 新加坡<br>Singapore       | 50              | 115/230       | 230/240            |
| 捷克<br>Czechoslovakia | 50              | 120/220        | 220/380            | 南非<br>South-africa     | 50              | 220/230       | 110/220<br>127     |
| 丹麦<br>Denmark        | 50              | 220            | 220/380            | 西班牙<br>Spain           | 50              | 127/220       | 220/380            |
| 埃及<br>Egypt          | 50              | 220            | 220/380            | 瑞士<br>Switzerland      | 50              | 220           | 220/380            |
| 芬兰<br>Finland        | 50              | 220            | 220/380            | 泰国<br>Thailand         | 50              | 110/220       | 220/380            |
| 法国<br>France         | 50              | 115/127/220    | 220/380            | 土耳其<br>Turkey          | 50              | 127/220/230   | 220/380            |
| 德国<br>Germany        | 50              | 110/220        | 220/380            | 英国<br>U.K.             | 50              | 240           | 240/415            |
| 希腊<br>Greece         | 50              | 220            | 220/380            | 越南<br>Viet-num         | 50              | 127/220       | 220/380            |
| 香港<br>Hongkong       | 50              | 110/200/230    | 220/380            | 加拿大<br>Canada          | 60              | 110/120       | 220/240/480        |
| 匈牙利<br>Hungary       | 50              | 220            | 220/380            | 哥伦比亚<br>Colombia       | 60              | 110/220       | 220/380            |
| 冰岛<br>Iceland        | 50              | 220            | 220/380            | 古巴<br>Cuba             | 60              | 115/120       | 240                |
| 印度<br>India          | 50              | 230            | 220/380<br>230/400 | 厄瓜多尔<br>Ecuador        | 60              | 120/127       | 208/220            |
| 印尼<br>Indonesia      | 50              | 127/220        | 220/380            | 韩国<br>Korea            | 60              | 100/200       | 200                |
| 伊拉克<br>Iraq          | 50              | 220            | 220/380            | 秘鲁<br>Peru             | 60              | 110/220       | 200                |
| 以色列<br>Israel        | 50              | 230            | 230/400            | 菲律宾<br>Philippines     | 60              | 110/220       | 220/440            |
| 意大利<br>Italy         | 50              | 127/220        | 220/380            | 美国<br>U.S.A.           | 60              | 120/240       | 240/480            |